



<b>PRODUCT NAME</b>	LED Touch Dimmer Box 1 Gang Faceplate, 12-24V 8A
<b>SKU</b>	LC-LF-8DIM
<b>PRODUCT URL</b>	<a href="#">Click Here</a>
<b>DESCRIPTION</b>	This PWM LED Light Dimmer uses a unique touch sensor to dim your LED lighting products. Touch the sensor to power on/off your LED lights, hold the sensor to dim or brighten them to desired level. Prior dimming levels are stored once the power is turned off and remain the same once the power is turned back on. It requires 12-24VDC input to operate, can handle 1 channel up to 8A or 96W at 12VDC or 192W at 24VDC. Wires are easily secured with screw down style connections. Can be used to dim LED lights, LED modules, LED light Ribbon, LED Wall Washers or for dimming any one color LED product with 12-24VDC constant voltage power requirements.
<b>CONTROLLER TYPE</b>	PWM
<b>SUPPLY VOLTAGE</b>	12VDC - 24VDC constant voltage
<b>OUTPUT</b>	1 channel
<b>DIMMING</b>	0 to 100%
<b>CONNECTION TYPE</b>	Common Anode
<b>DIMENSIONS</b>	4.5”T x 2.75”W (114.3mm T x 69.85mm W)
<b>OUTPUT CURRENT</b>	< 8A per channel (1 channel)
<b>OUTPUT POWER</b>	12VDC- 96 watts maximum 24VDC- 192 watts maximum
<b>WARRANTY</b>	1 year manufacturers

These specification are subject to change without notice.

This specification information is from the manufacturer of this product. Eco Light LED is not the manufacturer of this product.