



PRODUCT NAME	RGB LED Controller with RF Remote control
URL	Click Here
SKU	LC-LN-1RGBC-WR
DESCRIPTION	RGB LED Controller has 11 selectable modes. Includes a 4 button RF Remote, which allows you to control on/off, mode change and speed up or down. Remote control requires (1) 12V/23A type battery. Can be used to control RGB LED Lights, RGB LED Ribbon, RGB LED Modules and RGB LED Lighting.
MODES	<ul style="list-style-type: none"> ◇ 7 static colors: Red, Green, Blue, Yellow, Cyan, Pink, White ◇ 3 color jumpy change - RGB (instant change to next color) (speed is adjustable) ◇ 7 color jumpy change - RGBYCPW (instant change to next color) (speed is adjustable) ◇ 3 color fading change -RGB (speed is adjustable) ◇ 7 color fading change - RBPGYCW (speed is adjustable)
WORKING TEMP	0°F to 140°F (-18°C to 60°C)
SUPPLY VOLTAGE	12VDC constant voltage
OUTPUT	3 channels RGB
DIMMING	256 shades of grayscale per channel
CONNECTION TYPE	4 pin, 3 loop, common anode
DIMENSIONS	L 3.75" X W 3.5" X H 1" (L 95mm X W 89mm X H 26mm)
OUTPUT CURRENT	< 4A per channel (3 channels)
OUTPUT POWER	144 watts maximum
WARRANTY	1 year manufacturers

These specification are subject to change without notice. This specification information is from the manufacturer of this product. Eco Light LED is not the manufacturer of this product.
 Copyright © 2010 Eco Light LED