

SPECIFICATIONS

RGB LED Controller with 8 Button Remote



| | |
|------------------------|---|
| PRODUCT NAME | RGB LED Controller with 8 Button RF Remote control |
| SKU | LC-OL-6RGBC-WR |
| URL | Click Here |
| DESCRIPTION | RGB LED Lighting controller has 25 selectable modes. This control has an 8 button RF remote controller, which allows you to control on/off, color pause, mode change, brightness up or down and speed up or down. Remote and Receiver are paired using the same unique RF frequency. Remote control requires (1) 12V/23A type battery. Can be used to control RGB LED Lights, RGB LED Ribbon, RGB LED Modules and RGB LED Lighting. |
| MODES | <ul style="list-style-type: none">◇ 7 static colors: Red, Green, Blue, Yellow, Cyan, Pink, White◇ 3 color jumpy change - RGB (instant change to next color) (speed is adjustable)◇ 7 color jumpy change - RGBYCPW (instant change to next color) (speed is adjustable)◇ 3 color fading change -RGB (speed is adjustable)◇ 7 color fading change - RBPGYCW (speed is adjustable)◇ 7 color Strobe (colors strobe one at a time)◇ Red to Blue Crossfade, Blue to Green Crossfade and Green to Red Crossfade◇ All color fade in and fade out◇ Random Strobe Flash◇ Cycle thru all 24 functions |
| SUPPLY VOLTAGE | 12 - 24VDC constant voltage |
| OUTPUT | 3 channels RGB |
| CONNECTION TYPE | 4 pin, 3 loop, common anode |
| DIMENSIONS | L 4.75" X W 2.0" X H 1" (L 95mm X W 89mm X H 26mm) |
| OUTPUT CURRENT | < 4A per channel (3 channels) |
| OUTPUT POWER | 144W - 12VDC, 288W - 24VDC maximum |
| WARRANTY | 1 year manufacturers |

These specification are subject to change without notice. This specification information is from the manufacturer of this product. Eco Light LED is not the manufacturer of this product.
Copyright © 2010 Eco Light LED